

# การตั้งค่าโหมด Access Point บน AP Billion BIPAC 3301DL-T

- 1. พิมพ์ 192.168.2.1 ແລ້ວ∩ດ Enter
  - User = admin
  - Password = ใส่ตามรูปด้านล่าง (ถ้ามองไม่ชัดให้คลิกที่รูป จะเปลี่ยนแบบไปเรื่อยๆ แต่จะเป็นธหัสเติมเสมอ)

	Masaraa		<u> </u>
📄 🗋 Wireless A	C Router ×		
$\epsilon \rightarrow c$	🛈 ไม่ปลอดภัย   192.168.2.1/login.htm	☆	:
			-
BI	LLION <sub>e</sub>		
we	lcome		
	Log in with your Router's Username/Password		
	admin		
	â ·····		
	This is default password please text in the box.		
	Login		
			Ŧ



## 2. การตั้งค่ามี 2 วิธี ดังนี้

2.1. ตั้งค่าที่หน้า Quick Setup : Internet Connection Type เลือก Dynamic IP กต Save

<b>BILLION</b> .		English 🔻		Advanced
	Qu	ick Setup		
	Internet Connection Ty	уре		
Internet	Oynamic IP	Static IP O PPPoE		
	MAC Clone :			
	Wireless Setup			
Wireless	2.4G SSID :	true_home2G_872		
	Security : Password :	(Please enter 8-63 characters.)	ble	
	5G SSID :	true_home5G_872		
	Security :	Disable     Enab	ble	
	Password :	(Please enter 8-63 characters.)	<u>)</u>	
		Save		
http://www.billion.com				

#### 2.2. รอ Save สักครู่

<b>BILLION</b> .		English 🔻		
	Qui	ick Setup		
Internet	Dynamic IP     Save	pe J Successfully!		
	Wireless Setup			
Wireless	2.4G SSID :	true_home2G_872		
	Security :	Disable     Enat	ble	
	Password :	(Please enter 8-63 characters.)	, ,	
	5G SSID :	true_home5G_872		
	Security :	Disable     Enable	ble	
	Password :	(Please enter 8-63 characters.)	0	
http://www.billion.com		Save		



### 3. การตั้งค่าที่ Advanced :

#### 3.1. ท<sub>ี</sub>น้ำ Quick Setup คลิกปุ่ม Advanced

BILLION.	English Advanced							
Quick Setup								
Internet	Internet Connection Type							
	Dynamic IP     Static IP     PPPoE							
	MAC Clone :							
	Wireless Setup							
	2.4G SSID : true_home2G_872							
Wireless	Security : O Disable       Enable							
	Password : (Please enter 8-63 characters.)							
	5G SSID : true_home5G_872							
	Security : O Disable       Enable							
	Password : (Please enter 8-63 characters.)							
	Save							
http://www.billion.com								



#### 3.2. ท<sub>ี</sub>น้ำ **Status**

<b>BILLION</b>	5			Quick Setup
BiPAC 3301DL-T	WAN	V1.3.2832		
01-1-1-	Connection Type :	Dynamic IP (DHCP)		
Status	MAC Address :	60:03:47:3f:58:73		
Network	IP Address :	0.0.0.0		
IPV0	Subnet Mask :	0.0.0.0		
Wireless 2.40	Default Gateway :	0.0.0.0		
Pandwidth Control	Primary DNS :			
Enrwarding	Secondary DNS :			
<ul> <li>Access Control</li> </ul>	Link Status :	Disconnected		
Dynamic DNS	LAN			
Advanced	MAC Address :	60:03:47:3f:58:72		
System Tools	IP Address :	192.168.2.1		
Logout	Subnet Mask :	255.255.255.0		
English v	DHCP Server :	Enable	(192.168.2.33-192.168.2.64)	
	Wireless 2.4G			
	Wireless Status :	Enable		
	SSID :	true_home2G_872		
	Radio Mode :	AP		
	Authentication Type :	WPA2-PSK		
	Channel: 9			
	MAC Address : 60:03:47:3f:58:77			
	WPS Status : Enable			
	Wireless 5G			
	Wireless Status :	Enable		
	SSID : true_home5G_872			
	Radio Mode: AP			
	Authentication Type :	WPA/WPA2-PSK		
	Channel :	161		
	MAC Address :	60:03:47:3f:58:72		
WPS Status : Disable				



## 3.3. ไปที่ Network > WAN ตั้งค่า ดังนี้

- WAN Type เลือก Wired
- WAN Connection Type เลือก Dynamic IP
- na Save

BiPAC 3301DL-T	WAN Type	V1.3.2832
	WAN Type :  Wired	
Status	WAN Settings	
Network	WAN Connection Type : Dynamic IP (DHCP)	
WAN		
IPTV	Save	
Address Reservation		
Operation Mode		
► IPv6		
Wireless 2.4G		
Wireless 5G		
Bandwidth Control		
Forwarding		
Access Control		
Dynamic DNS		
Advanced		
System Tools		
Logout		
English 🔻		
to://www.billion.com		

### 3.4. รอ Save สักครู่

	WAN Type	
Status	WAN Type :  Wired  Wireless	
	WAN Settings WAN Connection Type : Dynamic IP (DHCP)    Advanced Saved Successfully!	
Forwarding     Forwarding     Access Control     Dynamic DNS     Advanced     System Tools     Logout		
English •		