

Pictures and Details of SERCOM T3 ST-244F



Front



Back



NAME	COLOR	DESCRIPTION
TEL 2 - 1	grey	Telephone port (RJ11)
LAN 4 - 1	yellow	Ethernet port (RJ45)
USB 3.0	blue	Flashdrive USB 3.0
USB 2.0	black	Flashdrive USB 2.0
RESET	black	Press and hold a button around 10 second to reset device
WPS	black	Connect Wi-Fi by WPS function
CATV	silver	F-connector port, 75 Ohm
POWER	black	Power in 12V, D2.1MM
ON/OFF	orange	Power on/ off

Top



bottom



Left




Right



LED status SERCOM T3 ST-244F

สถานะพร้อมใช้งาน



สถานะไม่พร้อมใช้งาน



LED	COLOR	STATUS	DESCRIPTION
PWR	green	on	on
		off	off
PON/LOS	green	off /off	Modem is off by OLT
	green	flashing /off	Modem is connecting to OLT
	green	on /off	Successfully connected to OLT
	red	off /on	No signal
INTERNET	green	on	Successfully obtained WAN IP
		flashing	Receiving-sending data
		off	No connection
LAN 1 - 4	green	on	Has device connected to LAN but no usage
		flashing	Receiving-sending data
		off	No connection
PHONE 1 - 2	green	on	VOIP successful connection
		flashing	Connecting
		off	VOIP is off / unsuccessful connection
2.4G	green	on	Wi-Fi 2.4G is on but no usage
		flashing	Receiving-sending data
		off	Wi-Fi 2.4G is off

5G	green	on	Wi-Fi 5G is on but no usage
		flashing	Receiving-sending data
		off	Wi-Fi 5G is off
WPS	green	on	Wait for pairing, LED is on around 1 minute and then off
		flashing	pairing
		off	WPS is turned off
USB	green	on	Have Flash drive connection
		off	No connection of Flash drive
CATV	green	on	CATV is working well, normal RF signal
		flashing	CATV is weak, weak RF signal
		off	CATV is off, or no signal

Contents in box:

- Router SERCOM T3 ST-244F
- Power Adapter
- 1 LAN cable
- User manual

